



Contents

Device	Part number	Quantity
Cable assembly RPC-2.40 ruggedized jack / RPC-2.40 plug	LU8-005-600	1
Cable assembly RPC-2.40 ruggedized jack / RPC-2.40 jack	LU8-006-600	1

Documents

Technical data sheet cable assembly:
RPC-2.40 ruggedized jack / RPC-2.40 plug
RPC-2.40 ruggedized jack / RPC-2.40 jack

LU8-005-XXX
LU8-006-XXX

Electrical data

Impedance	50 Ω
Frequency	DC to 50 GHz
Return loss	≥ 26 dB, DC to 4 GHz ≥ 17 dB, 4 GHz to 50 GHz
Insertion loss	≤ 2.80 dB at 50 GHz
Phase deviation:	
After 90° bending	≤ 1.3°, DC to 4 GHz ≤ 7.0°, 4 GHz to 50 GHz
Straight after 3x90° bending	≤ 1.0°, DC to 4 GHz ≤ 4.5°, 4 GHz to 50 GHz
Amplitude stability	≤ 0.03 dB, DC to 4 GHz ≤ 0.08 dB, 4 GHz to 50 GHz
Return loss stability	≥ 45 dB, DC to 4 GHz ≥ 35 dB, 4 GHz to 50 GHz
RF-leakage	≥ 100 dB up to 1 GHz

Mechanical data

Minimum bend radius	60 mm
---------------------	-------

Environmental data

Temperature range	-40°C to +85°C
2002/95/EC (RoHS)	compliant

While the information has been carefully compiled to the best of our knowledge, nothing is intended as representation or warranty on our part and no statement herein shall be construed as recommendation to infringe existing patents. In the effort to improve our products, we reserve the right to make changes judged to be necessary.

Draft	Date	Approved	Date	Rev.	Engineering change number	Name	Date
Herbert Babinger	23/01/07	Frank Tatzel	01/03/11	d00	11-0169	Krautenbacher J.	01/03/11
Rosenberger Hochfrequenztechnik GmbH & Co. KG P.O.Box 1260 D-84526 Tittmoning Germany www.rosenberger.de					Tel.: +49 8684 18-0 Fax: +49 8684 18-499 email: info@rosenberger.de		Page 2 / 2