


Digital wall dimmer for halogen and low-consumption lamps

Data brief



Description

The STEVAL-ILD004V1 evaluation board is designed to propose an innovative and low cost power topology for a light wall dimmer using two sensitive TS820-600FP SCRs and a single STGF10NC60KD IGBT to dim the following lamp types: 100 - 240 V halogen lamps, SELV halogen lamps through magnetic or electronic transformers, and new CFL and LED dimmable lamps.


Control of the board is achieved with the STM8S103F2 microcontroller.

Features

- Operation for 2-wire wall dimmer
- Leading-edge control only (compatible with all commonly-available lamps on the market)
- Operation at 110 V or 230 V line rms voltage and 50 Hz or 60 Hz line frequency
- Dimmable power range (higher power is possible with larger heatsink):
 - 3 W to 600 W for 230 V rms line
 - 3 W to 300 W for 110 V rms line
- Power efficiency @ 600 W - 230 V > 99%
- Standby losses @ 230 V < 0.3 W
- Short-circuit protection at startup
- Enhanced interface with push-buttons; soft-start and soft-stop; memory of last setting
- Compliance with EMC standards:
 - IEC 61000-4-5: criteria A for 2 kV surge
 - IEC 61000-4-4: criteria A for more than 2.5 kV
- Compliant with EN55015 with 600 W - 230 V halogen lamp
- RoHS compliant

1 Schematic diagram

Figure 1. STEVAL-ILD004V1 circuit schematic



GSPG0110D11515



2 Revision history

Table 1. Document revision history

Date	Revision	Changes
09-Jan-2013	1	Initial release.
06-Nov-2014	2	Figure 1: STEVAL-ILD004V1 circuit schematic has been updated.
02-Mar-2015	3	Updated: Feature Dimmable power range values.

IMPORTANT NOTICE – PLEASE READ CAREFULLY

STMicroelectronics NV and its subsidiaries ("ST") reserve the right to make changes, corrections, enhancements, modifications, and improvements to ST products and/or to this document at any time without notice. Purchasers should obtain the latest relevant information on ST products before placing orders. ST products are sold pursuant to ST's terms and conditions of sale in place at the time of order acknowledgement.

Purchasers are solely responsible for the choice, selection, and use of ST products and ST assumes no liability for application assistance or the design of Purchasers' products.

No license, express or implied, to any intellectual property right is granted by ST herein.

Resale of ST products with provisions different from the information set forth herein shall void any warranty granted by ST for such product.

ST and the ST logo are trademarks of ST. All other product or service names are the property of their respective owners.

Information in this document supersedes and replaces information previously supplied in any prior versions of this document.

© 2015 STMicroelectronics – All rights reserved